



Closing Resistor Selection Chart for *CapSwitcher*®

| kV | bank size in MVAR | closing resistor size |
|------|----------------------|--------------------------|
| 15.5 | 2 to 6 | 20 ohm |
| | 6.1 to 9 | 10 ohm |
| | 9.1 to 16 | 6 ohm |
| 27 | 3 to 6 | 30 ohm |
| | 6.1 to 16 | 20 ohm |
| | 16.1 to 27 | 12 ohm |
| 38 | 3 to 6 | 90 ohm |
| | 6.1 to 16 | 30 ohm |
| | 16.1 to 40 | 12 ohm |
| 48.3 | 4 to 18 | 40 ohm |
| | 18.1 to 48 | 20 ohm |
| 72.5 | 5 to 20 | 80 ohm |
| | 20.1 to 72 | 40 ohm |
| 123 | 15 to 40 | 150 ohm |
| | 40.1 to 75 | 75 ohm |
| | 75.1 to 130 | 37.5 ohm |
| 145 | 10 to 25 | 300 ohm |
| | 25.1 to 60 | 150 ohm |
| | 60.1 to 120 | 75 ohm |
| | 120.1 to 155 | 37.5 ohm |
| 170 | 18 to 30 | 300 ohm |
| | 30.1 to 75 | 150 ohm |
| | 75.1 to 181 | 75 ohm |

If you have a capacitor bank size not shown in the table above for one of these kV ratings please contact Southern States for closing resistor values and provide the bank size in MVAR and the kV rating of the installation.

Additionally, if desired Southern States can analyze a customer's specific installation and recommend a resistor size based upon that installation's specific requirements (i.e. kV rating of the installation, single bank switching or back-to-back switching, bank size, sequence in which banks are added [for back-to-back applications], etc.)

Southern States, LLC 30 Georgia Avenue Hampton, GA 30228 phone: 770-946-4562
 fax: 770-946-8106 e-mail: psdsales@southernstatesLLC.com website: www.southernstatesLLC.com

The Quality Name in High Voltage Switching

Publication No. PN807/809-CRSC-010707
 Printed in USA, January, 2007 • © 2007 Southern States, LLC

CapSwitcher is a registered trademark of Southern States, LLC