



EQUIPMENT CLARIFICATION – FUSE KITS:

- Southern States, LLC fuse kits were specifically designed for use in Southern States, LLC power fuse tubes – they cannot be installed in other manufacturer’s power fuse tubes.
- There are four speed ratios: PF and PFA= Slow Speed
PM and PMA= Medium Speed
PX and PXA= Fast Speed
PE and PEA= NEMA/EEI Standard Speed
- Characteristic curves are available upon request.
- Refer to the following chart to coordinate the application of the fuse kit with the fuse tube. Only those link ratings shown below beside their corresponding fuse tube rating can be installed in those fuse tubes (e.g. a 65 ampere link cannot be installed in a 200 amp tube, a 350 amp link cannot be installed in a 300 amp tube, a 100 amp link cannot be installed in a 200 amp tube, etc.)

KIT-TUBE COORDINATION CHART

<i>Kit Rating (Amperes)</i>	<i>Fuse Tube Rating (Amperes)</i>
1, 2, 3, 5, 7, 8, 10, 12.5, 15, 20, 25, 30, 40, 50, 60, 65, 75, 80, 100	100
125, 150 & 200	200
250 & 300	300
350 & 400	400

- When establishing the catalog number for fuse kits, use the type (letter code for speed) followed by kV rating and then amperage rating. Example: A fast speed kit rated 69 kV, 200 amps would be catalog number PX69200.
- Kits are packed one per box with estimated weight of two pounds each.

Southern States, LLC 30 Georgia Avenue Hampton, GA 30228 phone: 770-946-4562
fax: 770-946-8106 e-mail: sales@southernstatesLLC.com website: www.southernstatesLLC.com

The Quality Name in High Voltage Switching